Honeywell | Refrigerants

Orifice Sizing Guidelines

Technical Bulletin

Product: R422D Bulletin#: 000001 rev 1.0 Application: Residential R22 A/C systems with fixed orifice

Background: Some service technicians have experienced issues achieving the proper superheat and subcooling settings after converting R22 residential A/C systems with fixed orifice to R422D. If the technician is experiencing high superheat and low suction pressure with the system charged to 96% of the original charge the orifice may be undersized.

Resolution: Use the attached guideline to size orifice appropriately.



R422D Orifice Size Guideline

Tonnage	Orifice Size R22	Recommended Orifice Size R422D
1.5 Ton	0.053	0.059
2 Ton	0.059	0.065
2.5 Ton	0.071	0.076
3 Ton	0.076	0.082
3.5 Ton	0.080	0.086
4 Ton	0.082	0.090
5 Ton	0.090	0.099

*Note - this information is a guideline; other variables may impact system performance.

If you are still experiencing issues after changing the orifice please contact the Honeywell Technical Support Team @ 800-631-8138.

Download Complete Retrofit Guide @ www.honeywell-refrigerants.com

For more information:

Technical Support Team 800-631-8138. www.honeywell-refrigerants.com

Honeywell Refrigerants

115 Tabor Road Morris Plains, NJ 07950 Although Honeywell International Inc. believes that the information contained herein is accurate and reliable, it is presented without guarantee or responsibility of any kind and does not constitute any representation or warranty of Honeywell International Inc., either expressed or implied. A number of factors may affect the performance of any products used in conjunction with user's materials, such as other raw materials, application, formulation, environmental factors and manufacturing conditions among others, all of which must be taken into account by the user in producing or using the products. The user should not assume that all necessary data for the proper evaluation of these products are contained herein. Information provided herein does not relieve the user from the responsibility of carrying out its own tests and experiments, and the user assumes all risks and liabilities (including, but not limited to, risks relating to results, patent infringement, regulatory compliance and health, safety and environment) related to the use of the products and/or information contained herein.

Genetron is a registered trademark of Honeywell International Inc.



2/2017 © 2017Honeywell International Inc. All rights reserved.